

Ossia FW update from v1.x.x or higher to v1.3.3

Please note:

If your Ossia recorder running with v1.1 or lower, you will have to update to v1.2.6
As a first step – as this update is a deep platform change.

You can download v1.2.6 from: [Here](#)

- 1) This update will reset all setting to factory default. From this version and onwards – update will be applied via our servers directly from the Ossia OS & will keep the whole system setting.
- 2) This update is a “Flash burning process”, please extract the files from the “zip” pack
And copy to the root directory of USB pen FAT32 – MBR (Master boot record).

Insert the USB pen with files to the recorder & restart, this update will take about ~7 minutes.

Recorder will reboot several times during the update – do not interfere till the recorder will finish startup & will display the live view display with wizard screen.

- 3) In case of the device is not finishing update & normal startup process within 15 minutes, please disconnect & reconnect the power.

Best Regards,
Provision-ISR Technical support team.